

S1R72V27 QFP EVA BOARD RoHS Parts List

Note: A red letter of 'Reference' is nonimplement.

1つのReferencelに対してPartNameを複数指定しているものは、いずれかを使用してください。

PartName	Qty	Maker	Value	Rating	Tolerance	Reference
C1608CH1H090D	2	TDK	9pF	50V	0.5pF	C2,C3
GRM31MF11E105ZA01L	1	Murata Manufacturing	1uF	25V	+80/-20%	C4
EMF-160CDA220MD50G	1	Nippon Chemi-con	22uF	16V	20%	C7
EMVA160ADA220MD55G	1	Nippon Chemi-con	100uF	35V	20%	C8
EEE1VA101XP		Matsushita Electric Industrial				
EMVE350ADA101MF80G		Nippon Chemi-con				
GRM188R11H104JA01	11	Murata Manufacturing	0.1uF	50V	5%	C9,C10,C13,C19, C22,C24,C25,C26, C27,C28,C29
GRM188R31H104KA93D		Murata Manufacturing			10%	
GRM188R11H104JA01	1	Murata Manufacturing	0.1uF	50V	5%	C30
GRM188R31H104KA93D	2	Murata Manufacturing	10uF	16V	+80/-20%	C14,C16
EMK325F106ZH		Taivo Yuden		25V		
GRM32NF11E106ZA01L		Murata Manufacturing		25V		
EMK325F106ZH	2	Taivo Yuden	10uF	16V	+80/-20%	C11,C12
GRM32NF11E106ZA01L	2	Murata Manufacturing	10uF	25V		C18,C20
GRM21BB10J106ME01		Murata Manufacturing		6.3V	+10/-10%	
GRM188F11A105ZA01	5	Murata Manufacturing	1uF	10V	+80/-20%	C21,C23,C31,C32, C33
GRM188B31C105KA92D	2	Murata Manufacturing		16V	10%	CN2,CN3
WL-8-3	2	Mac Eight				CN4
NDP100-002-BF	1	Yamaichi Electronics				CN5
CAM-E42F-005-8904A	1	Mitsumi				CN6
DUSB-ARA42-T11A-FA	1	DDK				CN7
171825-4	1	AMP				CR1
FA-128(24MHz)	1	EPSON Toyocom	24MHz	CL=10pF	±30ppm /±50ppm(-40 ~	CRU1
SG-210SEB(48MHz/1.8V)	1	EPSON Toyocom	48MHz			DM1
HRW0202B	1	Renesas				IC1
S1R72V27F14E100	1	EPSON				IC2
MAX8586ETA+	1	Maxim				IC3
S1F78B20M1800	1	EPSON				IC4
R1170H331B-F	1	RICOH				JP2,JP6,JP7,JP13, JP14
JP-1-L	5	No_maker				JP8,JP9,JP10,JP11, JP12,JP15,JP18
JP-2-L	7	No_maker				JP3,JP16,JP17
JP-3-L	3	No_maker				L1,L2
DLW21SN900SQ2L	2	Murata Manufacturing	90			L3,L4,L5,L6
BLM21PG600SN1	4	Murata Manufacturing	60			R3,R17
MCR03EZJ104	2	ROHM	100k	1/16W	5%	R6
MCR03EZJ104	1	ROHM	100k	1/16W	5%	R4
MCR03EZJ102	1	ROHM	1k	1/16W	5%	R9,R10,R18, R19,R20
MCR03EZJ000	5	ROHM	0	1/16W	5%	R5
RR0816P-622-D	1	SSM	6.2k	1/16W	0.5%	R14
MCR03EZJ100	1	ROHM	10	1/16W	5%	R21
MCR03EZJ393	1	ROHM	39k	1/16W	5%	TP1,TP5,TP6,TP7, TP8,TP9,TP13
LC-33-S-Yellow	7	Mac Eight				TP21,TP22,TP23
LC-33-S-Yellow	3	Mac Eight				TP14,TP15,TP19
LC-33-S-Red	3	Mac Eight				TP16,TP17,TP18, TP20
LC-33-S-Black	4	Mac Eight				ZD1
RSB6.8S	1	ROHM				ZD2,ZD3
AVRL161A6R8GBA	2	TDK				JS1, JS2
JS-1	2	Mac Eight				