

Chemicals contained in products

Package-type

Epson Package name; **VSON-6PIN**

JEITA Package name; **(P-USON06-01.20x01.60-0.50)**

Lead frame plating; **Lead(Pb) Free**

Weight; **0.003 [g]** *Note1

Part	Subpart	Subpart weight [mg]	Substance name	CAS No.	Content ※2		Application
					[mg]	[ppm]	
IC Die	IC Die	0.15	Silicon	7440-21-3	0.15	999894	Base material
			Boron	7440-42-8	0.0000003	2	Dopant
			Phosphorus	7723-14-0	0.0000008	5	Dopant
			Aluminum	7429-90-5	0.000003	20	Metalization
			Arsenic *Note3	7440-38-2	0.000001	5	Dopant
			Fluorine *Note3	7782-41-4	0.0000003	2	Dopant
			Titanium *Note3	7440-32-6	0.000003	20	Metalization
			Molybdenum *Note3	7439-98-7	0.000003	20	Metalization
			Tungsten *Note3	7440-33-7	0.000005	30	Metalization
			Cobalt *Note3	7440-48-4	0.0000003	2	Metalization
	Stress buffer coat	0.003	Polyimide	-	0.003	1000000	Stress buffer coat *Note4
Package	Die Bonding material	0.017	Silver	7440-22-4	0.015	890000	Base material
			Epoxy resin	-	0.002	110000	Adhesive
	Lead Frame Plating	0.050	Tin	7440-31-5	0.049	975000	Solder
			Silver	7440-22-4	0.001	25000	Solder
	Lead Frame	1.3	Copper	7440-50-8	1.2	945000	Conductor
			Silver	7440-22-4	0.006	5000	Inner lead plating
			Others *Note5	-	0.064	50000	Additive
	Bonding Wire	0.010	Gold	7440-57-5	0.010	1000000	Conductor
	Mold resin	1.5	Epoxy resin	-	0.19	130000	Base material
			Antimony trioxide	1309-64-4	0.030	20000	Flame retardant
			Halogenated compound(brominations epoxy)	-	0.022	15000	Flame retardant
			Silica	60676-86-0/-	1.1	771000	Filler
Carbon black			1333-86-4	0.004	3000	Coloring agent	
Hardening chemical(ex:Phenol resin)			-	0.089	60000	Hardening chemical	
		Organic phosphorous compound	-	0.001	1000	Hardening accelerator	

Regarding the information of chemical substances

*Note1 The weight might be somewhat different depending on an individual built-in IC-chip specification like the size etc.

*Note2 Content data are estimated values based on supplier information and intended levels of content in product.

Actual measurements may vary from these values somewhat.

*Note3 Use or not-use of these substances depends on individual built-in IC-chip specification.

*Note4 The stress buffer coat may not be used depending on the individual model.

*Note5 The nickel, zinc, tin, silicon, iron, and the zinc oxide are included for the Cu type. And the carbon, silicon, and manganese are included for 42alloy type.