

Options of gdbmini*.ini

Flash erase and load command of gdbmini*.ini has some option commands. If needed, please add blue commands.

```
; set Target MCU
c17 model_path c:/EPSON/GNU17V3/mcu_model
c17 model 17***@NOVCCIN,NOREAD,NOWRITE,NOERASE
; connect to ICDmini, and start to control Target MCU
target icd icdmini*
; erase internal flash memory and load new program
load
```

Command	Explanation
NOVCCIN	TARGET VCC IN terminal of ICDmini Ver.3 is not connected to any lines. Please add this command.
NOREAD	No check on ahead whether new program is same as ROM data or not. If program always load to flash, please add this command to speed up the boot up time of debugger.
NOWRITE	No load program to flash memory.
NOERASE	No erase flash memory.

* Other commands and details of commands are described in below file.

C:\EPSON\GNU17V3\mcu_model\17***\fls\fls17***_readme_*.txt